



ITEM	QTY	SUPPLIER	MATERIAL DESCRIPTION	NOTES
1	1	CUSTOMER	Meter socket, 60A min, with breakers and receptacles, NEMA type 3R or better	A. Temporary service must be removed within 12 months of installation. B. All conduit and equipment must be plumb. C. Tamp earth around post and ensure post is firmly set, use staked 2" X 4" braces as shown if necessary. D. Customer is responsible for trenching to 2' from the source device. Cowlitz PUD will trench the last 2' and make the tie-in. E. Provide sufficient conductor to reach right front corner of transformer, plus an additional 5 feet. Leave coiled in trench. F. Temp service will be disconnected when permanent meter is installed unless otherwise approved. G. All grounding & bonding shall be in accordance with NEC Article 250 & WAC 296-46B-250. Contact Washington State L&I for more information.
2	1	CUSTOMER	Electrical inspection sticker	
3	1	CUSTOMER	4" x 4" min pressure treated wood post	
4	2	CUSTOMER	Conduit straps attached to post	
5	-	CUSTOMER	2" MIN ID ELEC SCH40 GRAY PVC conduit - length varies	
6	-	CUSTOMER	Secondary conductor (customer install)	

	STANDARDS		CONSTRUCTION STANDARDS		REV	DATE	DESCRIPTION
	PUBLIC UTILITY DISTRICT NO. 1 Cowlitz County, Washington 961 12th Avenue Longview, Washington		ELECTRICAL SERVICE REQUIREMENTS		0	3/3/25	Initial release
		UNDERGROUND TEMPORARY SERVICE		Designed	Checked	Standards Approved	Std/Dwg No.
		MJD	DPT			8-11	